

Secvest Wireless Panic Alarm Button

Art. no. FUAT50010

Page 1 of 1



- Suitable for discreet alarm triggering which does not attract attention
- It can be mounted under a counter, for example
- Tamper monitoring

Rapid and discreet help when panic sets in

The Secvest wireless panic alarm button is a detector in the Secvest wireless alarm system. At the touch of a button, a panic alarm can be easily and discreetly triggered to summon rapid assistance when it's needed. This alarm works even when the alarm panel is not armed.

Loud alarm or silent alert

You can decide for yourself whether a loud alarm is triggered locally or whether emergency services are silently notified. The optimal locations for the wireless panic alarm button are bedrooms and entrances, or under a sales counter.

Technical Data:

| | |
|----------------------------|---------------------------|
| Dimensions | (WxHxD) 85x85x52 mm |
| Battery type | Lithium battery – CR2477R |
| Width | 85 mm |
| Wireless alarm bandwidth | Narrow band |
| Radio frequency | 868,6625 MHz |
| Housing material | Thermoplastic material |
| Height | 85 mm |
| Length | 52 mm |
| Max. battery life | 2 year(s) |
| Max. operating temperature | 50 °C |

| | |
|-------------------------------|------------|
| Max. sending range (outdoors) | 100 m |
| Max. sending range (building) | 30 m |
| Min. operating temperature | -10 °C |
| Modulation | FM FM / AM |
| IP protection class | 32 |
| Security level | 2 |
| DC voltage supply | 3 V |
| Environmental class | II |