

Secvest Wireless Fire Alarm Button

Art. no. FUAT50020

Page 1 of 1



- Convenient on-wall mounting
- Suitable for inconspicuous and discreet alarming
- Tamper surveillance

The Secvest 2WAY wireless fire alarm button is a detector of the Secvest (or the Terxon with a wireless expansion module). By pressing the button, you can easily and quickly trigger a fire alarm. In the Secvest, the wireless fire button assigns a zone with the "fire" characteristic. This zone is monitored and the button will trigger an alarm even when the alarm panel is disarmed. In the system settings of the Secvest, you can define whether a call should be made to an emergency call center in addition to the acoustic and visual alarm. With corresponding batteries (3V lithium) the wireless fire button has a service life of approx. 24 months. The range is approx. 30 meters.

Technical Data:

Dimensions	(WxHxD) 85x85x52 mm
Battery type	3V CR2477N lithium battery
Width	85 mm
Radio frequency	868,6625 MHz
Transmission power	10
Housing material	Thermoplastic material
Height	85 mm
Length	52 mm
Max. battery life	2 year(s)
Max. operating temperature	50 °C
Max. sending range (outdoors)	100 m
Max. sending range (building)	30 m

Min. operating temperature	-10 °C
Modulation	FM FM / AM
Net weight	0.16 kg
Tamper monitoring	Yes
IP protection class	32
Security level	2
Voltage monitoring	Yes
DC voltage supply	3 V
Environmental class	II