

Secvest Wireless Indoor Siren

Art. no. FUSG50010

Page 1 of 1



- Designed to support of the alarm panel and wireless outdoor sounder acoustically
- Loud sounder (90 dB(A)@1 m)
- 12 V external power supply for operation without batteries (optional)
- Any number of indoor sirens can be integrated into the Secvest wireless alarm system

Reliable warning for indoor areas
The Secvest wireless indoor sounder is an optional Secvest accessory. As a purely acoustic sounder, it supports the wireless outdoor sounder and Secvest alarm panel with a signal tone of 90 dB sound pressure in the event of an alarm. The sounder and alarm panel communicate at 868.6625 MHz, a wireless frequency exclusively reserved for the security industry. The wireless indoor sounder can be powered by battery or a power supply unit. If batteries are used, the sounder has a service life of approx. 2 years. The sounder indicates when the battery life is coming to an end.

Technical Data:

Dimensions	(WxHxD) 122x208x60 mm
Connections	12V
Battery type	3x 1.5V LR20 battery
Width	122 mm
Radio frequency	868,6625
Housing material	ABS
Height	208 mm
Length	60 mm
Max. battery life	2 year(s)
Max. operating temperature	50 °C
Max. humidity	75 %
Max. receiving range (outdoors)	100 m

Max. receiving range (building)	30 m
Min. operating temperature	-10 °C
Modulation	FM FM / AM
Installation location	Indoors
Sound pressure	90 dB
IP protection class	54
Voltage monitoring	Yes
DC voltage supply	4,5/12 V
Environmental class	II